

KA7240

PS/2-USB VGA Virtual Media Console Module



The KA7240 Console Module offers secure access to the servers in a Matrix KVM Switch (<u>KM0932/KM0532</u>) from a PS/2 or USB console (monitor, keyboard, and mouse) up to 300 meters away. It provides an extra computer port for integration with a computer workstation, enabling users to seamlessly switch between the local computer and the servers in the Matrix KVM Switch. The KA7240 also features an intuitive graphical user interface, the Graphical OSD, with easy-to-use menus and icons that enable easy access and efficient management.

KA7240 has a built-in RS-232 port. Administrators can establish a serial terminal login to the Console Module in order to control the KVM port access for all consoles connected to switch – any console can be assigned to access any KVM port from a single interface point. In addition, an automatic skew compensation function corrects color phase and timing errors that occur over long distance transmissions.

Features

- One Combo Graphic Console Module can control a local computer and a matrix KVM switch (KM0932/KM0532)
- · Virtual Media Support
- Audio enabled
- · Enhanced video quality via automatic skew compensation support
- Supports PS/2 and USB keyboards and mice(Console)
- Switch between your workstation computer and the matrix KVM switch
- Graphical OSD-intuitive, easy-to-use graphical On Screen Display to manage servers
- RS-232 port login support permits an administrator to control the KVM port access for all consoles connected to switch any console can be assigned to access any KVM port from a single interface point
- Connects to matrix KVM switch via Cat 5e/6 cable
- Superior Video Quality 1920 x 1200 @ 60 Hz up to 200 meters; 1280 x 1024 @ 60 Hz up to 300 meters
- Manual video gain control for fine tuning
- Convenient computer selection via intuitive hotkey combinations or graphical OSD menus
- Firmware upgradeable

Specification

Computer Connections	1
Console Connections	1
Port Selection	GUI, Hotkey
Connectors	



Console Ports 2 x USB Type A Female (White) 1 x E-pin Mini-DIN Female (Green) 1 x SPH Jabe 15 Female (Blue) Virtual Media 1 x USB Type A Female (White) KVM Switch Ports 2 x RJ-45 Female (White) KVM Switch Ports 2 x RJ-45 Female (White) RS-232 1 x DB-9 Male (Black) Audio 2 x Mini Stereo Jack Female (Green) 2 x Mini Stereo Jack Female (Pink) 2 x Mini Stereo Jack Female (Pink) Power 1 x DC Jack Switches 1 x Slide Viduo dijustement 1 x Slide Viduo dijustement 1 x Slide Power 1 x Dusbutton (Local/Remote) LEOS 1 (Blue) Online 1 (Green) Local 1 (Orange)
1 x HDB-15 Female (Blue)Local Computer KVM Port1 x SPHD-17 Female (Yellow)Virtual Media1 x USB Type A Female (White)KVM Switch Ports2 x RJ-45 FemaleRS-2321 x DB-9 Male (Black)Audio2 x Mini Stereo Jack Female (Green) 2 x Mini Stereo Jack Female (Pink)Power1 x DC JackSwitchesFirmware Upgrade1 x SildeVideo Gain Adjustment2 x Pushbutton (Local/Remote)ElesPower1 (Blue)Online1 (Green)LCDa1 (Orange)
Port Include and an antipart of the second
KVM Switch Ports 2 x RJ-45 Female RS-232 1 x DB-9 Male (Black) Audio 2 x Mini Stereo Jack Female (Green) 2 x Mini Stereo Jack Female (Pink) Power 1 x DC Jack Switches I x DC Jack Firmware Upgrade 1 x Slide Video Gain Adjustment 2 x Pushbutton Selection 1 x Pushbutton (Local/Remote) LEDs I (Blue) Online 1 (Green) Local 1 (Orange) Remote 1 (Orange)
RS-232 1 x DB-9 Male (Black) Audio 2 x Mini Stereo Jack Female (Green) 2 x Mini Stereo Jack Female (Pink) Power 1 x DC Jack Switches 1 x DC Jack Firmware Upgrade 1 x Slide Video Gain Adjustment 2 x Pushbutton Selection 1 x Pushbutton (Local/Remote) LEDs 1 Power 1 (Blue) Online 1 (Green) Local 1 (Orange)
Audio 2 x Mini Stereo Jack Female (Green) Power 1 x DC Jack Switches
2 x Mini Stereo Jack Female (Pink) Power 1 x DC Jack Switches Firmware Upgrade 1 x Slide Video Gain 2 x Pushbutton Adjustment 2 x Pushbutton (Local/Remote) Selection 1 x Pushbutton (Local/Remote) LEDs 1 (Blue) Online 1 (Green) Local 1 (Orange)
SwitchesFirmware Upgrade1 x SlideVideo Gain Adjustment2 x PushbuttonSelection1 x Pushbutton (Local/Remote)LEDs1Power1 (Blue)Online1 (Green)Local1 (Orange)Remote1 (Orange)
Firmware Upgrade1 x SlideVideo Gain Adjustment2 x PushbuttonSelection1 x Pushbutton (Local/Remote)LEDs1 (Blue)Power1 (Blue)Online1 (Green)Local1 (Orange)Remote1 (Orange)
Video Gain Adjustment2 x PushbuttonSelection1 x Pushbutton (Local/Remote)LEDsPower1 (Blue)Online1 (Green)Local1 (Orange)Remote1 (Orange)
AdjustmentSelection1 x Pushbutton (Local/Remote)LEDsPower1 (Blue)Online1 (Green)Local1 (Orange)Remote1 (Orange)
LEDs Power 1 (Blue) Online 1 (Green) Local 1 (Orange) Remote 1 (Orange)
Power1 (Blue)Online1 (Green)Local1 (Orange)Remote1 (Orange)
Online 1 (Green) Local 1 (Orange) Remote 1 (Orange)
Local 1 (Orange) Remote 1 (Orange)
Remote 1 (Orange)
Emulation
Keyboard / Mouse PS/2; USB (PC, Sun, Mac)
Video 1920x1200@60Hz (200 m); 1280x1024@60Hz (300 m)
Scan Interval 1-240 Seconds
Power Consumption DC5.3V:6.12W:48BTU/h
 Note: The measurement in Watts indicates the typical power consumption of the device with no external loading. The measurement in BTU/h indicates the power consumption of the device when it is fully loaded.
Environmental
Operating 0 - 50°C Temperature
Storage Temperature -20 - 60°C
Humidity 0-80% RH, Non-condensing
Physical Properties



Housing	Metal
Weight	1.26 kg(2.78 lb)
Dimensions (L x W x H)	22.71 x 17.15 x 5.48 cm (8.94 x 6.75 x 2.16 in.)
Note	For some of rack mount products, please note that the standard physical dimensions of WxDxH are expressed using a LxWxH format.

Diagram



ATEN International Co., Ltd.

3F., No.125, Sec. 2, Datong Rd., Sijhih District., New Taipei City 221, Taiwan Phone: 886-2-8692-6789 Fax: 886-2-8692-6767 www.aten.com E-mail: marketing@aten.com



© Copyright 2015 ATEN® International Co., Ltd. ATEN and the ATEN logo are trademarks of ATEN International Co., Ltd. All rights reserved. All other trademarks are the property of their respective owners.