

---

## CS72E

2-Port PS/2 VGA Slim KVM Switch



The KVM (Keyboard, Video, Mouse) switch is a control unit that allows access to two computers from a single console (keyboard, monitor, and mouse). With its custom designed connectors, the significantly reduces the number of ports required for a 2 port KVM switch. The design features a custom SPHD-15 male connector for the keyboard, video, and mouse, and SPHD-15 female connectors for the cables that connect the switch to the computers.

### Features

- One PS/2 console controls 2 computers.
- Compact, modern case for convenient attractive placement.
- Custom connector layout.
- Power on detection - automatically switches to the first powered on port.
- Computer selection via front panel pushbuttons and hotkeys.
- Superior video quality - up to 2048 x 1536; DDC2B.
- Supports Microsoft IntelliMouse and the scrolling wheel on most mice.
- Auto Scan function to monitor computer operation.
- Non-powered.
- OS Support: Windows 2000, Windows XP, [Windows Vista](#), LINUX and FreeBSD

## Specifications

Computer Connections	2
Port Selection	Hotkey, Pushbutton
Connectors	
Console Ports	1 x SPHD-15 Male (Yellow)
KVM Ports	2 x SPHD-15 Female (Yellow)
Power	1 x DC Jack
Switches	
Ports	2 x Pushbutton
LEDs	
Selected	2 (Green)
Emulation	
Keyboard / Mouse	PS/2
Video	2048 x 1536 @ 60Hz; DDC2B
Scan Interval	5 seconds
Power Consumption	DC5V:0.30W:6BTU/h  Note: <ul style="list-style-type: none"><li>● The measurement in Watts indicates the typical power consumption of the device with no external loading.</li><li>● The measurement in BTU/h indicates the power consumption of the device when it is fully loaded.</li></ul>
Environmental	
Operating Temperature	0-50°C
Storage Temperature	-20-60°C
Humidity	0~80% RH, Non-condensing
Physical Properties	
Housing	Metal
Weight	0.32 kg ( 0.7 lb )
Dimensions (L x W x H)	12.50 x 8.15 x 2.50 cm (4.92 x 3.21 x 0.98 in.)
Note	For some of rack mount products, please note that the standard physical dimensions of WxDxH are expressed using a LxWxH format.

Diagram

