
UC100KMA

PS/2 to USB Adapter with Mac support (30cm)



UC100KMA is a signal converter with a 30cm cable. It can convert signals of PS/2 devices (keyboard and mouse) into USB signals, and supports multiple operating systems to fulfill the needs of users.

Features

- Two PS/2 devices (keyboard and mouse) to USB Interface converter
- Supports PS/2 mice and microsoft IntelliMouse
- Hotkey selection for OS and keyboard language supports
- Compatible with KVM Switches
- USB specification compliant
- External power adapter not required
- Easy installation - no software required
- OS Support: Windows 2000, Windows XP, [Windows Vista](#), LINUX, Mac, Sun and FreeBSD

Specification

Connectors	
USB Port	1 x USB Type A Male (White)
PS/2 Keyboard	1 x 6-pin Mini-DIN Female (Purple)
PS/2 Mouse	1 x 6-pin Mini-DIN Female (Green)
LEDs	
Link	2 (Green)
Cable Length	30 cm
Platforms	Windows 2000/XP/Vista/Linux Mac OS 8.6 or Higher SUN Solaris 8
Data Rate	12 Mbps
Power Mode	Bus Powered (via the USB cable)
Environmental	
Operating Temperature	0–50°C
Storage Temperature	-20–60°C
Humidity	0–80% RH, Non-condensing
Physical Properties	
Housing	Plastic
Weight	0.08 kg (0.18 lb)
Dimensions (L x W x H)	9.15 x 4.70 x 2.50 cm (3.6 x 1.85 x 0.98 in.)
Power Consumption	DC5V:0.374W:6BTU/h Note: <ul style="list-style-type: none">● The measurement in Watts indicates the typical power consumption of the device with no external loading.● The measurement in BTU/h indicates the power consumption of the device when it is fully loaded.
Note	For some of rack mount products, please note that the standard physical dimensions of WxDxH are expressed using a LxWxH format.

Diagram

